SimpleChIP® Human HoxA1 Intron 1 Primers Cell Signaling



✓ 500 μl (250 PCR reactions)

Orders 877-616-CELL (2355)

orders@cellsignal.com

Support 877-678-TECH (8324)

info@cellsignal.com


Web www.cellsignal.com

rev. 02/24/16

For Research Use Only. Not For Use In Diagnostic Procedures.

Applications Species Cross-Reactivity Primer Anneal/Extension **PCR Product Length** ChIP Н 65°C 181 bp

Description: SimpleChIP® Human HoxA1 Intron 1 Primers contain a mix of forward and reverse PCR primers that are specific to intron 1 of the human Homeobox A1 (HoxA1) gene. These primers can be used to amplify DNA that has been isolated using chromatin immunoprecipitation (ChIP). Primers have been optimized for use in SYBR® Green quantitative real-time PCR and have been tested in conjunction with SimpleChIP® Enzymatic Chromatin IP Kits #9002 and #9003 and ChIP-validated antibodies from Cell Signaling Technology®. The homeobox gene clusters are silenced by members of the polycomb family.



SimpleChIP® Human HoxA1 Intron 1 Primers were tested on DNA isolated from cross-linked cells using the SimpleChIP® Enzymatic Chromatin IP Kit (Magnetic Beads) #9003. Real-time PCR was performed in duplicate on a serial dilution of 2% total input DNA (20 ng, 4 ng, 0.8 ng, and 0.16 ng) using a real-time PCR detection system and SYBR® Green reaction mix. The PCR amplification efficiency (E) and correlation coefficient (R2) were calculated based on the corresponding threshold cycle (C_{τ}) of each dilution sample during 40 cycles of real-time PCR (95°C denaturation for 15 sec, 65°C anneal/extension for 60 sec).


Storage: Supplied in nuclease-free water at a concentration of 5 μM (each primer is at a final concentration of 5 μM). Store at -20°C.

Directions for Use:

- 1. Label the appropriate number of PCR tubes or PCR plates compatible with the model of real-time PCR machine to be used. PCR reactions should be performed in duplicate and should include a tube with no DNA to control for contamination, and a serial dilution of a 2% total input chromatin DNA (undiluted. 1:5, 1:25, 1:125), which is used to create a standard curve and determine amplification efficiency.
- 2. Add 2 μl of the appropriate ChIP DNA sample to each tube or well of the PCR plate.
- 3. Prepare a master PCR reaction mix as described below. Add enough reagents for two extra reactions to account for loss of volume. Add 18 μ l of the master PCR reaction mix to each PCR reaction tube or well of the PCR plate.

Volume for 1 PCR Reaction (20 ul) Reagent Nuclease-free H₂O $6 \mu l$ 5 μM SimpleChIP® Primers $2 \mu l$ 2X SYBR® Green Reaction Mix 10 µl

- 4. Start the following PCR reaction program:
 - a. Initial Denaturation: 95°C for 3 min.
 - b. Denaturation: 95°C for 15 sec.
 - c. Anneal and Extension: Primer-specific temp. for 60 sec.
 - d. Repeat steps b and c for a total of 40 cycles.
- 5. Analyze quantitative PCR results using software provided with the real-time PCR machine.



PCR product melting curves were obtained for real-time PCR reactions performed using SimpleChIP® Human HoxA1 Intron 1 Primers. Data is shown for both duplicate PCR reactions using 20 ng of total DNA. The melt curve consists of 80 melt cycles, starting at 55°C with increments of 0.5°C per cycle. Each peak is formed from the degradation of a single PCR product.

SYBR® Green is a registered trademark of Molecular Probes, Inc.